

SURFACE 24V

EMERGENCY LIGHTING

MANUAL - EN

Technical specifications

Power: 2W	Lifetime: >45.000 uur
Voltage: 24V AC/DC	IP class: IP20
Dimmable: No	



Safety instructions

- This product should be installed and maintained by a certified installer.
- Keep this device away from children and unauthorized users.
- Risk of electroshock when opening the cover. Touching live wires can cause life-threatening electroshocks. Do not disassemble or open the housing yourself. Let the fixture be repaired by an installer.
- This luminaire does not have a built-in device to disconnect it from the electric mains. Make sure to electrically isolate the luminaire before installation or maintenance activities are performed. Do not crimp the power cord and protect it against damage. Warning! If the power cord is damaged, it must be replaced.
- Caution: possibly hazardous optical radiation emitted from this product.
- Do not look at operating lamp. Eye injury may result.
- Caution: device heats up during use.
- Do not use the luminaire with a cracked or broken protective shield.
- Disconnect immediately from the mains. The protective shield is not replaceable.
- All electrical installations must be carried out according to IEE wiring regulations.

ISO 7010 pictograms

Pay attention to the correct orientation and position of the pictograms.

Installation

- Turn the power off, before starting the installation or wiring.
- Open the housing by pushing a flat screwdriver into the two horizontal slots in the housing. The mounting plate of the housing pops out.
- Take out the plastic bag with clips from the fixture.
- Install the mounting plate at the desired location with plugs and screws.
- Wire up the luminaire in accordance to IEE wiring regulations.
- Click the connector of the mounting plate on the internal print plate.
- After wiring close the housing by pushing it over the mounting plate. Press the housing carefully until you hear "click".
- Remove the protective foil from the pictograms and hanging plate.
- Use the clips to mount the pictograms on the hanging plate.
- Make sure the printed side of the pictogram is installed inwards against the hanging plate.

General usage

- Keep this device away from extreme temperatures.
- Protect the product for shocks and brute force.
- All modifications of the device are forbidden for safety reasons.
- Damage caused by user modifications to the device is not covered by the warranty.
- Using the device in an unauthorised way will void the warranty.
- Damage caused by disregard of certain guidelines in this manual is not covered by the warranty and the dealer will not accept responsibility for any ensuing defects or problems.
- Use the original packaging if the device is to be transported.
- Keep this manual for future reference.